

www.ezhometech.com

13. HLS with .m3u8 output

Step1:

- Click Channel Button and Click More icon
- Select HLS option to Constant Bitrate (internal transcoder)

HTTP Live Streaming :	 Disabled Constant Bitrate (Internal transcoder) Constant Bitrate (External transcoder) Adaptive Bitrate (External transcoder) 	
Mobile Bitrate:	0	kbps
SD Bitrate:	0	kbps
HD Bitrate:	0	kbps
Video Format :	h264 🔻	
Audio Format :	aac 🔻	
Encoding Speed : Save	ultrafast	T

Step2:

- Input URL into Safari for signle channel or all channels
 - Single channel:

Syntax: http://ip_address:port/chx.m3u8?u=xxxx:p=xxxx

Ex.: http://192.168.0.10:8000/ch1.m3u8?u=test:p=1234

• All channels:

Syntax:

http://ip_address:port/server/get_user_chlist?username=xxxx:password=xxxx:ch _list_type=m3u8

Ex.

http://192.168.0.8:17000/server/get_user_chlist?username=test:password=1234: ch_list_type=m3u8

• Download m3u8 ch list from panel